

EUROLITE LCD-4/S Dimmer

4-channel lighting controller

- 4 channels
- Fade Time fader with LED for adjusting the step time
- Master-fader with LED for adjusting the total output level
- Audio-fader with LED for adjusting the music sensitivity
- Flash-button per channel and master-flash (Full On-button)
- LED-display of all modes
- 0/10 V-output via one 8-pin DIN-socket
- 42 built-in programs
- Dimmer: Manual control of the channels via sliders
- Full On: all channels can be switched on together
- Program speed adjustable via speed-fader or Tap Sync-button
- Sound-control via external signal or integrated microphone
- Sound to light via RCA-socket
- Outputs via 4 safety sockets
- 19"-dimensions with 3 units



Power supply:	230 V AC, 50 Hz ~
Max. power output:	3680 W
Max. current:	16 A
Number of control-channels:	4
Max. output/channel:	1150 W
Max. current/channel:	5 A
Integrated programs:	42
Sound-control:	via built-in microphone or via audio-input
Audio-input:	RCA-socket
Audio-sensitivity:	0.1 - 1 V
Output sockets:	4 safety sockets
Fuse:	4 x F 6,3A, 250 V
Dimensions (WxDxH):	482 x 145 x 132 mm
	19" mounting dimensions with 3 u
Minimum mounting depth:	230 mm
Weight:	4.5 kg